



### Control directly from your mobile device with ROSE Connect!

It includes a Dedicated Remote Control Application that allows users to conveniently control and smartly manage ROSE devices. The remote control application works on various platforms including iPhone, iPad, Android phone, and PC.

 <b>Android Download</b>		 <b>iOS Download</b>	
-----------------------------	--	-------------------------	--

Specification		
Display	8.8inch TFT LCD & Capacitive Touch Screen(MIPI-DSI)	
OS	Customized Android 7.1 based ROSE OS	
Size	278(W) x 202(D) x 76(H)mm	
Weight	3.2kg	
Power	Input Voltage : AC100-120V, 220-240V 50/60Hz Input Power : 50W	
Audio	Supported Codec	WAV, FLAC, ALAC, AIFF, WMA, MP3, OGG, APE, DFF, DSF, AAC, CDA, AMR, APE, EC3, E-EC3, MID, MPL, MP2, MPC, MPGA, M4A
	Supported Sampling Rate	PCM : 8kHz~768kHz(8/16/24/32bit per Sample) DSD : DSD64(2.8MHz)/DSD128(5.6MHz)/DSD256(11.2MHz)/DSD512(22.5792MHz)
	MQA	Full Decoding
Video	Supported Codec	ASF, AVI, MKV, MP4, WMV, MPEG-1, MPEG-2, MPEG-4 H.263, H.264, H.265, VC-1, VP9, VP8, MVC,H.264/AVC (Base/Main/High/High10 profile@level5.1 upto 4Kx2K@30fps) H.265/HEVC (Main/Main10 profile@ level 5.1 High-tier up to 4Kx2K@60fps)
	CPU	Hexa Core Dual-core Cortex-A72 up to 1.8GHz Quad-core Cortex-A53 up to 1.4GHz
H/W	Memory	LPDDR3 4GB
	GPU	Mali-T864 GPU, OpenGL ES 1.1/2.0/3.0/3.1, OenVG1.1, OpenCL, DX11
	DAC	ES9038Q2M
	Oscillator	High Precision Femto Clock
Preout	DAC Chip	ES9038Q2M(ESS) x 1 (Single Stereo Design)
	Output Level	Max 2.3Vrms , Unbalanced
	THD	0.0002% (1kHz 2.3Vrms Unbalanced output)
	THD + N	0.0003% (1kHz 2.3Vrms Unbalanced output)
	IMD	-102dB (SMPTE 4:1, 60Hz:7KHz)
	Signal to Noise Ratio	116dB (A-wt)
	Dynamic Range	Max 126dB (CCITT filter)
	Stereo Crosstalk	Better than -133dB, 20-20kHz
	Output Frequency Response	20Hz to 20,000(+/-0.5dB)
	Output Impedance	100Ω
Network Connectivity	Bluetooth	A2DP Sink, AVRCP v1.3
	WiFi	802.11b/g/n/a/ac (2.4GHz/5GHz)
	Ethernet	10/100/1000 Base-T (1Port)
	Digital In	Optical x 1, Coaxial x 1
I/O Port	Digital Out	Optical x 1, Coaxial x 1
	Analog In	Line in x 1
	Analog Out	Pre-out (Unbalanced RCA x 1)
	Headphone Out	Connection for 3.5mm headphones, Unbalanced 1Vrms (32Ω)
	USB Audio In	USB B Type 2.0
	USB Audio Out	USB A Type 3.0
Storage	HDMI	HDMI 2.0 x 1 (up to 3840 x 2160 / 60Hz)
	USB	USB 3.0 x 2
	SSD	SATA 3.0, SSD x 1
	SATA	4TB
	USB	10TB
Connectivity	File System	NTFS / exFAT / FAT32
	Room Ready	Support
	Spotify Connect	Support
	Streaming Protocol	Airplay / DLNA / Bluetooth
	Network Storage	SMB / FTP/ WebDav
CD Ripping	Support(By external USB ODD)	

A/S Inquiry : 1899-6042 (57 Sinchon-ro, Sujeong-gu, Seongnam-si, Gyeonggi-do)

[www.hifirose.com](http://www.hifirose.com)

# Complete HiFi Network Streamer RS250

## Beyond Audio, HiFi ROSE



rose

# Complete HiFi Network Streamer



## High Resolution Sound

PCM32bit/768kHz, Native DSD512(22.4MHz), FLAC, MQA Full Decoder



### Linear Power Circuit Design

The full linear power supply provides a clean and reliable power supply to the CPU and audio output circuits. It applies the full linear power unit and shielding and blocks noise that can be delivered to sensitive DAC for best sound playback.



### Flagship DAC Designed for Single Stereo

RS250 with built-in ESS flagship DAC (ES9038 Q2M) provides low-noise, low-distortion, and ultra-high-resolution sound and rich analog density through unique processing that supports PCM32bit/768kHz and Native DSD512 (22.5792MHz).




### Hi-Res Certified

HiFi ROSE is a device that has been certified by the Japan Audio Society (JAS) as "High-Resolution Audio."



### MQA Full Decoder

MQA is a technology that enables seamless streaming of original master sound with small file sizes. The device supports the highest MQA Full Decoder function, so you can play your music in studio master quality.



### Streaming Music Services

TIDAL, Qobuz, Bugs, ROSE Tube, Internet Radio and Podcasts are available in-app in ROSE Connect (Remote Control App), and Spotify Connect, Airplay, Bluetooth A2DP, DLNA, and RoonReady features are also available.

\*In-app services will continue to be upgraded.



### CD Playback / CD Ripping

You can play and rip the music on a CD by connecting an external CD drive via USB. You can extract the sound source from CDs as WAV or FLAC files and save it to SSD or USB.

## Smart and Convenient Controls



### 8.8" Wide Touch Screen

The IPS Multi-Touch panel with a high-resolution, wide viewing angle provides an intuitive and convenient interface. You can play albums and music videos on the front display.



### Dedicated Remote Control Application

It includes a Dedicated Remote Control Application that allows users to conveniently control and smartly manage ROSE devices. The remote control application works on various platforms including iPhone, iPad, Android phone, and PC.




### Bluetooth Remote Control

You can control the device simply and easily using the dedicated Bluetooth remote control with an excellent grip.



## Various Menu Features

In addition to audio and video, it is equipped with features including Rose Tube, Rose Podcast, and Internet Radio, so you can subscribe to and listen to contents around the world in real time via network streaming, and you can set radio channels as alarm sounds through various clock faces.




## Plays Ultra HD 4K Video

You can enjoy Ultra HD 4K video or ROSE Tube video files on a large display from a connected storage device (USB, external hard drive, SSD, etc.) via HDMI connection. Now, you can get the vivid experience of an opera house at home.



## Network Streaming

Enjoy real-time streaming services through DLNA, Airplay, and ROSE Connect.



## Wired or Wireless Connections to Various Devices

**In/Out Port** USB 3.0, USB Audio In/Out, HDMI, Coaxial In/Out, Analog In/Out, OPTICAL In/Out

**Connectivity** Bluetooth, DLNA, Airplay, Spotify Connect, Roon Ready

